

# WISE-PaaS FAQ

Category	EPD	Date	2021/5/12
Keyword	EPD-023, EPD-053, EPD-132		

# Question:

How to OTA the EPD device FW?

# Steps:

#### Step 1. When log in the ePaper Manager, click "OTA" and select "Storage". Then click "edit".

→ œ ŵ	0 🔏 ≒ 172.22.20.12:8	080/inain/storage		🖂 🏠	IN 🖸 🕸
ePape Mana	er Iger			*	4° • 8
	Storage Management				
•					
	Storage Name *	Туре	Security	Max Connections	Operation
2	localStorage	±15	NONE	□5 ↓30	3 🔽 📰
1 OTA J Upgradu	6			Total ISudo:	_ 3 1 2
Packag     Stomge	2				

# Step 2. Modify the Domain IP as the server IP.

( <del>(</del> ) =	C 🌚 🛛 🖉 🛱 172.22.2	20.12 1080/main/storage	··· 🖂 🕁	11/00 ⊛ Ξ
Ŧ	Care Paper Monapar		×.	4 · 8 · · · ·
	G Storage Management			
	TTT Contracting and the second second			
=	+			
	Storage Name *	Edit FTP Storage	Aax Connections	Operation
<b>M</b> E	a locationage	* Storage Name	mis ⊊ 30	
-		Sector (Construction)	Total I https:/	
۵		• Security O NONE O FTPS O FTP	PES	
×		* Domai 172.22.20.12		
0				
0,		Port 21		
*		* Account Name use1		
		Báck Confirm		

Step 3. Select "OTA" and select "Package". Then click "Upload"

**ADVANTECH** 

Enabling an Intelligent Planet

€)- ≡	୧୦୦ ଜ୍ୟା	er ger	0 🔏 😂 1	72.22.20.12:8080/m	ain/package			등 ☆	ĸ 🖉		© ≡
0	localStora	ge( •	± Upload €	3 @ Remove						<b>C</b> Syn	c Files
		No.	Туре	Version	OS	Arch	Storage	Name			
m	0	1	EPD132R	2.0.8.0	n/a	n/a	localStorage	EPD132R-v2.0.8.0-25e6b3dfbdfcbb8e17f6	7		>
		2	EPD023R	1.0.3.0	n/a	n/a	localStorage	EPD023R-v1.0.3.0-7843b492baa20881a5	9		>
	0	3	EPD023B	1.0.5.0	n/a	n/a.	localStorage	EPD0238-v1.0.5.0-7098ce529e121d040fa	a		>
	0	4	EPD053R	1.0.6.0	n/a	n/a	localStorage	EPD053R-v1.0.6.0-934bcc52aa3ea409717	9		>
-	0	5	EPD023R	1.0.2.0	nta	n/a	localStorage	EPD023R-v1.0.2.0-fca745f104a74219310	oe		>
0		6	1840	1.0.4.0	n/a	n/a	localStorage	1840-v1.0.4.0-a94ae72e4c6dd09f4b513fa	3		>
1	1 0	7	EPD053R	1.0.5.0	n/a	n/a	localStorage	EPD053R-v1.0.5.0-535548b0e8b11c8aab	3		>
3	ΟΤΑ		EPD053R	1.0.4.0	n/a	n/a	localStorage	EPD053R-v1.0.4.0-3aadd3f1209fc27b82b	9		>
Q <sup>5</sup>	t Upprad	. 2	1840	1.0.2.0	n/a	n/a.	localStorage	1840-v1.0.2.0-f3bf1796afd7959894fe1945	9		>
	Packag	e	EPD053R	1.0.1.0	n/a	n/a	localStorage	EPD053R-v1.0.1.0-38a3323be7ad558f6e9	ib		>
-	A Storage		EPD053R	1.0.3.0	n/a	n/a	localStorage	EPD053R-v1.0.3.0-7ea82f58941eb86ac3b	i4		>
		14	EPD053R	1.0.0.0	n/a	n/a	localStorage	EPD053R-v1.0.0.0-632027a0082d6e0962	b.,.		>
							S ▼ Up EPD132R-v2.0.	oload file to "localStorage(FTF 8.0-25e6b3dfbdfcbb8 255кв	P)" Stora	ge 10(	20

# Step 4. Select the FW which you want to upload to ePaper Manager.

(+) -)	C ŵ		@ # ≈ 172.22.2	0.12:8080/main/parkage	6	する	IN ED 49 Ξ
H.	ePaper Monoger	Cat	vel	File Upload		Q Open	🖉 🛛 🔒 mot
			Recent Home Documents Downloads Music Pictures Videos UBUNT	File Upload         Image: State	<ul> <li>▲ Size</li> <li>260.9 kB</li> <li>56 bytes</li> <li>58 bytes</li> <li>183 bytes</li> <li>25.9 kB</li> <li>1.9 kB</li> <li>66 bytes</li> </ul>	Madified 21 = 2020 18 :* 27 fi 2 = 10 += 2020 10 = 2020 28 + 2020 24 =	C Sync Files
			_			All Files •	

Step 5. Click "OTA" and click "Upgrade"

AD\ANTECH

Enabling an Intelligent Planet

Account	1001	Group	- Diffait -	Status		Mode	Device
t Up	grade Management						
3							
	Name 🍵	Panel Type	Processing	Software	Package	Program	FW Version
- 4	EPD_Hub	12	<b>4</b> 0 €0	0/0	0	N/A	EPD_HubSooUD\ 101
1	mon mouter-483078	2	<b>₩ 0 © 0</b>	0/0	0	N/A	20975620
UTA 1	:g-02cc44	EPD-132R	40 20	0/0	0	N/A	E132R500XMV20 7
A DE LA DESCRIPTION DESCRIPTION DE LA DESCRIPTION DE LA DESCRIPTION DE LA DESCRIPTION DE LA DESCRIPTION DESCRIPTION DE LA DESCRIPTION DE LA DESCRIPTION DE LA DESCRIPTION DE LA DESCRIPTION DESCRIPTION DE LA DESC	2	EPD-132R	Ψ 0 ⊃ 0 0	0/0	0	N/A	E132R500XMV20 7
1 Upgrade	-g-02d88c						

Step 6. Click the "Device" which you want to do OTA. Click " and select your EPD model.

Finally, select the FW version and click "OK". The OTA will start to do FW upgrade.

<ul> <li>Choose Action</li> <li>Upgrade</li> <li>Download</li> <li>Deploy</li> <li>Anne</li> <li>Choose Package</li> <li>Choose Package</li> <li>Choose Package</li> <li>Choose Package</li> <li>EPD_Hub</li> <li>EPD_Hub</li> <li>EPD_Hub</li> <li>EPD_Hub</li> <li>EPD_Tag-St</li> <li>EPD_Tag-St</li> <li>EPD_Tag-St</li> <li>EPD_Stag-St</li> <li>EPD_Sta</li></ul>	T.	Ingrade Mai	Upç	grade	e Ope	ration				
Image: Second		pgrade ma	hoose Acti	on						
Name       Choose Package       am       FW Version         Image: EPD_Hub       Image: EPD_132R       Image: EPD_132R       Image: EPD_132R         Image: Ima	3	2	Upgrade	01	Downloa	d 🛛 🔘 Depl	oy			
Image: EPD_Hub       Image: EPD132R       Image: EPD132R       Image: EPD_Hub       Image		Name	hoose Pack	age					am	FW Version
Version         OS         Arch         Optimized         Storage         Name         20975624           1         2.08.0         3.         r/a         false         localStorage         EPD132R- v2.0.8.0-25e6b3rlfbdfcbb8e17/67e564999ef5e.zip         E132R500XM E132R500XM 7           I         EPD0.7ag-0         I         EPD023R         E132R500XM 7         E132R500XM 7           I         EPD07ag-5         I         EPD023R         I         I         E132R500XM 7	E S	LEPD_Hub	EPD1	32R						EPD_HubS00UD
•         2.080         3         n/a         false         localStorage         EP0132R V2.0.8.0-25e6b3/thdtcbis8e17/67e564999ef5e.zip         E132RS00XM 7           •         •         EPD0238         •		A EPO-Route	Version	OS	Arch	Optimized	Storage	Name		20975620
Image: Constraint of the problem in the problem i			0 2.0.8.0	3	rva	false	localStorage	EP0132R- v2.0.8.0-25e6b3dfbdfcbb8e17f67e564999ef5e.zip		F132DS00XMV2
EPD-Tag-0 D EPD023R E132R500XM 7 D EPD053R 2097561		EPD-Tag-02	C EPD02	38						7
EPD-Tag-3. EPD053R 20075610		EPD-Tag-0	C EPD02	3R						E132RS00XMV2
	= 0	EPD-Tag-3,	O EPDOS	3R						20975618
L 1840			1840							