



RSB-4680

Release Note

Released Version:V230008
Released Date: 2021-04-02

Advantech Co., Ltd.

<http://www.advantech.com/>

ABSTRACT

This document describes how to use diagnostic tool for board functionality verification.

Copyright Notice

This document is copyrighted, 2012, by Advantech Co., Ltd. All rights are reserved. Advantech Co., Ltd. reserves the right to make improvements to the products described in this manual at any time. Specifications are thus subject to change without notice.

No part of this manual may be reproduced, copied, translated, or transmitted in any form or by any means without the prior written permission of Advantech Co., Ltd. Information provided in this manual is intended to be accurate and reliable. However, Advantech Co., Ltd., assumes no responsibility for its use, or for any infringements upon the rights of third parties which may result from its use.

All the trademarks of products and companies mentioned in this data sheet belong to their respective owners.

Copyright © 1983-2012 Advantech Co., Ltd. All Rights Reserved

For more information on this and other Advantech products please visit our website at :

<http://www.advantech.com>

Part No.

Version: 1.00

Printed in Taiwan 2021-04-02

1. Hardware Information

CPU: RK3288

2. Software Information

Debian10

3. Release Version

Rev	Date	Description	Release by
DIV230008	2021-04-02	The first release	Yunjin.Jiang

4. Add New Features

5. Function Test

Module	Test Steps	Result
CPU Cores	CPUinfo under kernel cat /proc/cpuinfo grep "processor" wc -l	PASS
CPU Speed	A53 cat /sys/devices/system/cpu/cpufreq/policy0/cpuinfo_max_freq	PASS
CPU DVFS	cat /sys/devices/system/cpu/cpufreq/policy0/scaling_cur_freq	PASS
memeory	check meminfo capacity cat /proc/meminfo	PASS
	Check memory clock under kernel cat /sys/class/devfreq/dmc/cur_freq	PASS
	memtester 1000M 5	PASS
GPU	check gpu working using benchmark or web http://webglsamples.org	PASS
	Check GPU clock /sys/class/devfreq/ffa30000.gpu/cur_freq	PASS
VPU	Play video and check decoding mode	PASS
PMIC	1.8V/3.3V/5V voltage,reset,poweroff	N/A
DEBUG	config as normal uart port	PASS

UART	System debug message output and input	PASS
SD	SD card read/write	PASS
eMMC	emmc read/write	PASS
SPI Flash	On Board read/write	PASS
	PIN header	N/A
I2C	i2cdetect i2cget i2cset	N/A
LAN	RGMII ping -c 500 172.21.170.48	PASS
UART	ttySx: rs232_loop /dev/ttyS0 /dev/ttyS1 115200 h 100 /dev/ttyS1 OK /dev/ttyS2 OK /dev/ttyS3 OK /dev/ttyS4 OK	PASS
	ttyUSBx: rs232_loop /dev/ttyUSB0 /dev/ttyUSB1 115200 h 100	PASS
USB2.0	USB disk read/write cat /sys/bus/usb/devices/5-1/speed	PASS
	UVC camera preview/capture/video	PASS
USB OTG	Host mode	PASS
	Slave mode	PASS
HDMI	Audio Play	PASS
	Multiple resolution:720p@60Hz/1080p@60Hz/4k@30Hz/	PASS
LVDS	Backlight adjustment	PASS
	lvds-g070vw01	PASS

	lvds-g150xgel05	N/A
	lvds-g215hvn01	N/A
VGA		PASS
RTC	date 2021-03-01 17:11:22 hwclock -w	PASS
Audio Codec	play and record	PASS
GPIO	GPIO input/output	PASS
Watchdog	cat /dev/watchdog	PASS
Power Button	Power off	PASS
SW reboot	reboot	PASS
M.2		N/A
		N/A
mini PCIE	EC25	PASS
	WIFI & BT W172	PASS
tools	mac_write	PASS
	RKDevTool	PASS
	SDDiskTool	PASS

6. Performance Test

Module	Test Steps	Result	Remark
Benchmark	apt install hardinfo cpu:benchmarks---cpu blowfish(eg:5.91s) 2D:benchmarks---gpu drawing(eg:5418) 3D:taskset -c 4-5 glmark2-es2	PASS	cpu: blowfish 6.33 2D: cpu drawing 4030.37 3D: hdmi only, glmark2 52

lan	throughput: pc: iperf3 -s ARM: iperf3 -c 192.168.1.1 -i 5 -t 180	PASS	[5] 0.00-180.00 sec 19.7 GBytes 941 Mbits/sec sender [5] 0.00-180.00 sec 19.7 GBytes 941 Mbits/sec receiver
	Packet Lost: pc: iperf3 -s ARM: iperf3 -c 192.168.1.1 -u -b 80M -t 43200 -l 60k	PASS	[ID] Interval Transfer Bitrate Jitter Lost/Total Datagrams [5] 0.00-43200.00 sec 167 GBytes 33.1 Mbits/sec 0.000 ms 0/2911168 (0%) sender [5] 0.00-43200.00 sec 167 GBytes 33.1 Mbits/sec 0.131 ms 0/2911168 (0%) receiver
SD	read: dd if=/dev/sd of=/dev/zero bs=1M count=4 conv=fsync write: dd if=/dev/zero of=/dev/sd bs=1M count=4 conv=fsync	PASS	4194304 bytes (4.2 MB, 4.0 MiB) copied, 0.193995 s, 21.6 MB/s 4194304 bytes (4.2 MB, 4.0 MiB) copied, 0.429177 s, 9.8 MB/s
eMMC	read: dd if=/dev/mmcblk0 of=/dev/zero bs=1M count=4 conv=fsync write: dd if=/dev/zero of=/dev/mmcblk0px bs=1M count=4 conv=fsync	PASS	4194304 bytes (4.2 MB, 4.0 MiB) copied, 0.0182596 s, 230 MB/s 4194304 bytes (4.2 MB, 4.0 MiB) copied, 0.103465 s, 40.5 MB/s
usb2.0	read: dd if=/dev/sda of=/dev/zero bs=1M count=4 conv=fsync write: dd if=/dev/zero of=/dev/sda bs=1M count=4 conv=fsync	PASS	4194304 bytes (4.2 MB, 4.0 MiB) copied, 0.128409 s, 32.7 MB/s 4194304 bytes (4.2 MB, 4.0 MiB) copied, 0.254651 s, 16.5 MB/s
	UVC Camera Power on detect 200 times Preview 2 hours	PASS	
BurnIn	Run BurnIn.sh 4H	PASS	